

Feature

- Forward Current: 100mA
- Reverse voltage: 30V
- Low forward voltage
- Low leakage current
- Trench MOS barrier Schottky technology
- Ultra Small mold type. (DFN0603-2L)




DFN0603-2L(Bottom View)

Applications

- Low current rectification
- Voltage clamping
- Protection circuits
- Ultra high-speed switching



Circuit Diagram



Marking (Top View)

Mechanical Characteristics

- Mounting position: Any
- Qualified max reflow temperature:260°C
- Device meets MSL 1 requirements
- DFN0603-2L without plating

Electrical characteristics per line@25°C

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Forward voltage	V_F		0.30	0.35	V	$I_F=1.0mA$
Forward voltage	V_F		0.35	0.40	V	$I_F=10mA$
Forward voltage	V_F		0.47	0.55	V	$I_F=100mA$
Reverse current	I_R			0.3	μA	$V_R=10V$
Reverse current	I_R			0.5	μA	$V_R=30V$
Junction Capacitance	C_j		15		pF	$V_R=0V, f=1MHz$

Absolute maximum rating@25°C

Parameter	Symbol	limits	Unit
Reverse voltage (DC)	V_{RM}	30	V
Average rectified forward current	I_o	100	mA
Forward current surge peak (60Hz 1cyc)	I_{FSM}	2.0	A
Operating Junction temperature Range	T_j	-55 to 125	°C
Storage temperature Range	T_{stg}	-55 to 125	°C

Typical Characteristics




Fig.1 Typical Forward Characteristics




Fig 2.Leakage Current







Fig 3.Capacitance vs. Reverses voltage

Solder Reflow Recommendation



Remark: Pb free for 260°C; Pb for 245°C

Product dimension (DFN0603-2L)



Suggested PCB Layout


Unit: mm

Dim	Millimeters		
	MIN	Typ.	MAX
A	0.28	0.30	0.35
A1	0	0.02	0.05
b1	0.13	0.18	0.23
b2	0.14	0.19	0.24
c	0.05	0.10	0.15
D	0.55	0.60	0.65
e	0.35BSC		
L1	0.025BSC		
L2	0.035BSC		
E	0.25	0.30	0.35
L	0.20	0.25	0.30
h	0	0.05	0.10


Ordering information

Device	Package	Reel	Shipping
PSBD2XD30V01	DFN0603-2L (Pb-Free)	7"	12000 / Tape & Reel

Load with information




IMPORTANT NOTICE

 and **Prisemi**[®] are registered trademarks of **Prisemi Electronics Co., Ltd** (Prisemi) ,Prisemi reserves the right to make changes without further notice to any products herein. Prisemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Prisemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. “Typical” parameters which may be provided in Prisemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including “Typicals” must be validated for each customer application by customer’s technical experts. Prisemi does not convey any license under its patent rights nor the rights of others. The products listed in this document are designed to be used with ordinary electronic equipment or devices, Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Website: <http://www.prisemi.com>

For additional information, please contact your local Sales Representative.

©Copyright 2009, Prisemi Electronics

 **Prisemi**[®] is a registered trademark of Prisemi Electronics.

All rights are reserved.